

The QUAD FM4



At the touch of a button the Quad FM4 gives access to a variety, breadth and quality of programme material that the most dedicated gramophile would find difficult to equal. Indeed the emotional satisfaction which can be gained from a well engineered live broadcast is second only to being at the concert itself. An FM tuner is thus an essential piece of equipment for any serious listener to music.


The FM4, as one might expect from Quad is deceptively simple and original. Good ergonomics and advanced electronics are combined to produce a tuner with exceptional audio performance and ease of handling.

The Quad FM4 is designed as an adjunct to a high quality music system. As such emphasis in design is placed upon obtaining audio performance from a reasonable input signal rather than the ultimate in selectivity. Performance of the

FM4 is such that given adequate signal strength, it makes no audible contribution to the incoming programme, and provides absolutely faithful reproduction of the original transmission.

The only controls on the FM4 are an on/off switch, tuning knob and eight pushbuttons which are used to store and recall stations in the tuner's memory. The tuned frequency is shown in figures and an ingenious bar graph display provides simultaneous information of signal strength and centre tuning. A specially developed dedicated microprocessor makes all decisions about muting and AFC and also controls the tuner's memory in which are stored the preset stations.

Operating the Quad FM4 is simplicity itself. Once programmed it is only necessary to press one of the seven preset buttons for the wanted station to be tuned in perfectly.



Programming stations into the tuner's memory is very straightforward. The desired frequency is located by rotating the tuning knob, which will have conspicuous advantages for anybody who has tried to find a station using pushbuttons to track up and down. The bar graph confirms that the station is correctly tuned and being received with sufficient signal strength to give acceptable signal to noise.

Pressing the appropriate preset station button and the manual tune button simultaneously stores the station in the tuner's memory. And that's all there is to it. AFC and muting is taken care of automatically. Stereo over-ride, required if the signal is very weak, is achieved by switching the Quad 44 to MON and adjusting the balance control for minimum noise.

Programmes will remain stored in the tuner's memory almost indefinitely

provided that the tuner is used once in a while, and for up to five years even if it is disconnected from the mains.

When switched on the tuner remembers the station last used and automatically reverts to it.



THE QUAD FM4 TUNER

SPECIFICATION

Frequency range	88-108MHz
Sensitivity - 30dB quieting	Mono 1 μ V
50dB quieting	Mono 2.7 μ V
	Stereo 25 μ V
Full Limiting	<1 μ V
Signal/Noise - Input signal 1kHz at 1mV. A weighted	Mono 76dB
	Stereo 70dB
Distortion Input signal - 1kHz \pm 75kHz	Mono 0.15%
	Stereo 0.15%
\pm 25kHz	Mono 0.05%
	Stereo 0.10%
Selectivity	53dB
Capture Ratio	2.5dB
IF Rejection	100dB
AM Suppression	60dB
Image Rejection	80dB
Pilot Tone Suppression	60dB
Crosstalk at 1kHz	40dB
Frequency Response - 20-15kHz	+0 -1dB
Output Level 30% Modulation	100mV
Source Impedance	100 Ω
Recommended Load Impedance	>20k Ω
Aerial Input	75 Ω unbalanced
De-emphasis	50 μ Sec or 75 μ Sec
Power Input	100-125 or 200-250V. 50-60Hz 6VA.
Dimensions	321mm wide 64mm high 207mm deep.
Weight	3Kg.

Quad Electroacoustics Ltd.,
Huntingdon, Cambs., PE18 7DB.
Telephone: (0480) 52561

QUAD 
for the closest approach
to the original sound



The Quad FM4 with the Quad 44 control unit.